



Public address kit for small shop GGM PAKIT4S



This public address kit GGM PAKIT4S is dedicated for small installation like shops, restaurants, hairdressers etc...
It is composed of one desktop amplifier 60 watts power output and 4 ceiling speakers with maximum consumption of 6 watts each.

The amplifier integrates SD/USB slot to play MP3 files from external memory (USB stick or memory card) It also embed radio FM tuner to broadcast radio. it supports also bluetooth connectivity to connect devices (mobile phone, tablet) and play internal memory. This amplifier integrates 2 RCA input to connect external sources.



In the front panel you can connect microphone with jack 6.35 input to broadcast voice messages.

* it is possible to extend the number of ceiling speaker to 4 with a maximum power consumption of 6 watts for each.

Specifications

Amplifier features :

- Power output 60 W ; Ouput speaker 100 V
- SD/USB port for mp3 file reading
- Bluetooth connectivity
- Radio FM Tuner
- 2 RCA input for external sources
- 1 mic input (jack 6,35 mm TSR)
- Desktop format

Speaker features:

- Protection IP20
- Enclosure : ABS and metal grille
- Type of speaker : coaxial
- Size of speaker: 5" + 1.5"
- frequency response : 80 Hz ~ 20 kHz
- Power taps: 0,75/1,5/3/6 W @ 100 V
- Impedancy : 13,3 k?, 6,7 k?, 3,3 k?, 1,7 k?



- Sensitivity : 88 dB
- Cut-out : 180 mm
- Dimension : 202x98 mm
- Weight : 0,6 kg